



60.000
digits

○○●
ABS

DAKkS

IR

GOSSEN METRAWATT

GMC-I Messtechnik GmbH
Südwestpark 15 ■ 90449 Nürnberg ■ Germany
Phone: +49 911 8602-111 ■ Fax: +49 911 8602-777

www.gossenmetrawatt.com ■ info@gossenmetrawatt.com



METRAHIT **E-SERIES**
TRMS SYSTEM MULTIMETER

E-BASE	E-TECH	E-SPECIAL	E-XTRA	Functions
■	■	■	■	Voltage measurement
■	■	■	■	TRMS AC and AC+DC
1kHz	20kHz	20kHz	100kHz	Bandwidth (TRMS)
300kHz	300kHz	300kHz	1MHz	Frequency measurement
Clamp	10(16)A	10(16)A	10(16)A	Current measurement
	■	■	■	Low-pass filter (1 kHz)
		■	■	Capacitance measurement
■	■	■	■	IR interface
			■	Data storage
			■	Mains connection
15	21	23	26	Measuring functions

Printed in Germany. Subject to change without notice. 3/10.13 3-337-208-03

E-SERIES

Selecting a digital multimeter from the METRAHIT E series provides you with an ultramodern, top quality measuring instrument – as well as unique precision: With a resolution of 60,000 counts and a basic accuracy level of 0.05%, these instruments offer maximized results reliability. They cover a broad range of demanding measuring tasks thanks to their great variety of functions, and they're distinguished in every day use by an innovative, ergonomic design.

Features

- Resolution: $\pm 60,000$ counts, 4 $\frac{1}{2}$ -place
- 3 connector jacks with patented automatic blocking sockets (ABS)
- Furnished with DAkkS calibration certificate
- System integration with IR interface
- Large illuminated display with 15 mm characters
- TRMS AC/DC function
- Voltage measurement with a basic accuracy of $\pm 0.05\%$ (VDC)
- Automatic / manual measuring range selection
- Automatic storage of measured values DATA/MIN/MAX
- Communication with a PC via METRAwin10 software
- Measuring categories: 1000 V CAT III and 600 V CAT IV (ESPECIAL 600 V CAT II)



METRAHIT|E**BASE**



METRAHIT|E**TECH**



METRAHIT|E**SPECIAL**



METRAHIT|E**EXTRA**



METRAHIT|E**BASE**

- 15 multimeter functions
- Current measurement via current sensor clamps with adjustable transformation ratio from 1 mV:1 mA to 1 mV:1 A

HIGH RESOLUTION
60,000 digits

METRAHIT|E**TECH**

- 23 multimeter functions
- Adjustable clamp factor for measurement via current sensor clamps and current transformer clamps
- Broad range capacitance measurement
- Current ranges optimized for measuring transformers

HIGH RESOLUTION
60,000 digits

METRAHIT|E**SPECIAL**

- 21 multimeter functions
- Special multimeter for connection to current transformers
- Without fuse link in order to rule out any risk of interrupting the transformer circuit
- Adjustable transformation ratio with automatic calculation of the current value
- Low-pass filter can be activated in order to eliminate interference signals

HIGH RESOLUTION
60,000 digits

METRAHIT|E**EXTRA**

- 26 multimeter functions
- Direct current measurement from 10 nA to 10 A, 16 A for short periods
- Temperature measurement with Pt100(0) resistance sensors
- Broad range capacitance measurement
- Frequency and duty cycle measurements at 2 to 5 V signals up to 1 MHz
- Data storage (64,000 measured values)

HIGH RESOLUTION
60,000 digits

Scope of Delivery

- 1 multimeter
- 1 pair of safety measurement cables (1.5 m) with 4 mm test probes, 1000 V CAT III, 600 V CAT IV (KS17-2)
- 2 batteries 1.5 V, type AA
- 1 set of short-form operating instructions, English/German
- 1 CD ROM (multilingual operating instructions, METRA VIEW demo software)
- 1 DAkkS calibration certificate
- 1 protective rubber holster
- 1 HC20 hard case