



**NEW**



The APS-7000E series linear AC power supply is 2U height and the output frequency range of the series is 45–500Hz. The maximum rated output for APS-7050E is 500VA, 310Vrms, 4.2Arms; and APS-7100E is 1000VA, 310Vrms, 8.4Arms. The APS-7000E series comprises six measurement and test functions (Vrms, Irms, F, Ipk, W, PF), and provides user interface similar to that of AC Power Meter. The APS-7000E series, via switching many sets of current levels to increase small current measurement resolution, is ideal for the LED industry and standby mode power consumption test. To meet the test criteria of line voltage fluctuation often seen in consumer electronics, the APS-7000E series not only supplies a stable AC source, but also features Test mode to handle special purpose or abnormal voltage and frequency. Test mode features ten sets of memory to simulate power outage, voltage increase, and voltage drop. The series is ideal for users to produce grid power transient waveform to verify electronic product operation under adverse conditions.

## APS-7000E Series

### FEATURES

- 4.3 inch TFT-LCD Display
- Output Capacity :  
APS-7050E(500VA,310Vrms,4.2/2.1Arms)  
APS-7100E(1000VA,310Vrms,8.4/4.2Arms)
- Measurement Function Comprises Voltage, Current, Power, Current(peak), Frequency, Power Factor
- 10 sets of the Test Mode Simulate Power Transient Output
- 10 sets of Preset Allow Users to Store Ten Settings
- OVP, OCP and OTP Protection
- Variable Voltage, Frequency and Current Limiter
- Universal Power Inlet



APS-7100E Rear Panel



APS-7050E Rear Panel

### APPLICATIONS

- The Broad Power Output Range of The Series is Ideal for Various Power Supply Manufacturers
- The Development of Electronic Components and Testing Applications for Manufacturers
- Incoming Quality Control and R & D Applications
- Small AC Current Measurement Applications

## SPECIFICATIONS

Model	APS-7050E		APS-7100E	
Power Rating	500VA		1000VA	
Output Voltage	0 ~ 310.0 Vrms		0 ~ 310.0 Vrms	
Output Frequency	45.00 ~ 500.0 Hz		45.00 ~ 500.0 Hz	
Maximum Current (r.m.s)	0~155Vrms	4.2A	0~155Vrms	8.4A
	0~310Vrms	2.1A	0~310Vrms	4.2A
Maximum Current (peak)	0~155Vrms	16.8A	0~155Vrms	33.6A
	0~310Vrms	8.4A	0~310Vrms	16.8A
Total Harmonic Distortion (THD)	≤0.5% at 45 ~ 500Hz (Resistive Load)			
Crest Factor	≥4			
Line regulation	0.1% (% of full scale)			
Load regulation	0.5% (% of full scale)			
Response time	<100us			
<b>SETTING</b>				
Voltage	Range	155Vrms/310Vrms/Auto		
	Resolution	0.01V at 0.00 ~ 99.99Vrms; 0.1V at 100.0 ~ 310.0Vrms		
	Accuracy	±(0.5% of setting+2 counts)		
Frequency	Range	45 ~ 500Hz		
	Resolution	0.01Hz at 45.00 ~ 99.99Hz/0.1Hz at 100.0 ~ 500.0Hz		
	Accuracy	±0.02% of setting		
<b>MEASUREMENT</b>				
Voltage(RMS)	Range	0.20 ~ 38.75Vrms/38.76 ~ 77.50 Vrms/77.51 ~ 155.0Vrms/155.1 ~ 310.0Vrms		
	Resolution	0.01V at 0.00 ~ 99.99Vrms; 0.1V at 100.0 ~ 310.0Vrms		
	Accuracy	±(0.5% of reading + 2 counts)		
Frequency	Range	45 ~ 500Hz		
	Resolution	0.01Hz (at 45Hz~99.99Hz)/0.1Hz (at 100Hz~500.0Hz)		
	Accuracy	±0.1Hz		
Current(RMS)	Range	2.00 ~ 70.00mA/60.0 ~ 350.0mA/0.300 ~ 3.500A/3.00 ~ 17.5A		
	Resolution	0.01mA, 0.1mA, 0.001A, 0.01A		
	Accuracy	±(0.6% of reading+5 counts); 2.00~350.0mA/±(0.5% of reading+5 counts); 0.350~3.500A/±(0.5% of reading+3 counts);3.500~17.50A		
Current(Peak)	Range	0.0 ~ 70.0A		
	Resolution	0.1A		
	Accuracy	±(1% of reading+1 count)		
Power(W)	Resolution	0.01W, 0.1W, 1W		
	Accuracy	±(0.6% of reading + 5 counts); 0.20~99.99W; ±(0.6% of reading + 5 counts); 100.0 ~ 999.9W		
	Accuracy	±(0.6% of reading + 2 counts); 1000~9999W		
Power Factor	Range	0.000~1.000		
	Resolution	0.001		
	Accuracy	±(2% of reading + 2 counts)		
<b>GENERAL</b>				
Number of Preset	10 (0~9 Numeric keys)			
Protection	OCP, OPP, OHP and Alarm			
<b>ENVIRONMENT CONDITIONS</b>				
Operation Temperature	0 ~ +40°C			
Storage Temperature	-10 ~ +70°C			
Operating Temperature	20 ~ 80% RH (No Condensation)			
Storage Humidity	80% RH or less(No Condensation)			
<b>INPUT</b>				
Input Power Source	1φ AC 115/230Vac ±15%			
<b>DIMENSIONS</b>				
	430(W) x 88(H) x 400(D) mm; Approx. 24Kg		430(W) x 88(H) x 560(D) mm; Approx. 38Kg	

Specifications subject to change without notice. PS-7000EGD1DH

## ORDERING INFORMATION

APS-7050E 500VA AC Power Source  
 APS-7100E 1000VA AC Power Source

## ACCESSORIES

CD ROM (User Manual x 1), Power Cord (Region Dependent),  
 Mains Terminal Cover Set, GTL-123 Test Lead

## OPTIONAL ASSESSORIES

GRA-423 APS-7000E Rack Mount Kit

Global Headquarters

### GOOD WILL INSTRUMENT CO., LTD.

No.7-1, Jhongsing Road, Tucheng Dist., New Taipei City 236, Taiwan  
 T +886-2-2268-0389 F +886-2-2268-0639  
 E-mail: marketing@goodwill.com.tw

China Subsidiary

### GOOD WILL INSTRUMENT (SUZHOU) CO., LTD.

No. 521, Zhujiang Road, Snd, Suzhou Jiangsu 215011 China  
 T +86-512-6661-7177 F +86-512-6661-7277  
 E-mail: marketing@instek.com.cn

Malaysia Subsidiary

### GOOD WILL INSTRUMENT (M) SDN. BHD.

27, Persiaran Mahsuri 1/1, Sunway Tunas,  
 11900 Bayan Lepas, Penang, Malaysia  
 T +604-6309988 F +604-6309989  
 E-mail: sales@goodwill.com.my

Europe Subsidiary

### GOOD WILL INSTRUMENT EURO B.V.

De Run 5427A, 5504DG Veldhoven, THE NETHERLANDS  
 T +31 (0)40-2557790 F +31 (0)40-2541194

U.S.A. Subsidiary

### INSTEK AMERICA CORP.

5198 Brooks Street Montclair, CA 91763, U.S.A.  
 T +1-909-399-3535 F +1-909-399-0819  
 E-mail: sales@instekamerica.com

Japan Subsidiary

### TEXIO TECHNOLOGY CORPORATION.

7F Towa Fudosan Shin Yokohama Bldg., 2-18-13 Shin  
 Yokohama, Kohoku-ku, Yokohama, Kanagawa,  
 222-0033 Japan  
 T +81-45-620-2305 F +81-45-534-7181  
 E-mail: info@texio.co.jp

Korea Subsidiary

### GOOD WILL INSTRUMENT KOREA CO., LTD.

#1406, Ace Hightech-City B/D 1Dong,  
 Mulla-Dong 3Ga 55-20, Yeongduengpo-Gu, Seoul, Korea  
 T +82-2-3439-2205 F +82-2-3439-2207  
 E-mail: gwinstek@gwinstek.co.kr

# GW INSTEK

Simply Reliable



[www.gwinstek.com](http://www.gwinstek.com)



[www.facebook.com/GWInstek](https://www.facebook.com/GWInstek)