

The offer: 3 True RMS ranges!

	F201	F402	F203	F404	F604	F205	F406	F606	F407	F607	
Display resolution	6000 cts	10,000 counts	6,000 cts	10,000 counts		6,000 cts	10,000 counts		10,000 counts		
Measurements displayed	x1		x1			x1			x3		
Display backlighting	●		●			●			●		
Acquisition method	AC TRMS		AC / DC TRMS			AC / DC / AC + DC TRMS			AC / DC / AC + DC TRMS		
Auto AC/DC (V or/and A)	●		●			●			●		
A	AC	600 A	1000 A	600 A	1,000 A	2,000 A	600 A	1,000 A	2,000 A	1,000 A	2,000 A
	DC			900 A	1,500 A	3,000 A	900 A	1,500 A	3,000 A	1,500 A	3,000 A
	AC+DC						900 A peak	1,500 A peak	3,000 A peak	1,500 A peak	3,000 A peak
V	AC	1,000 V	1,200 V	1,000 V	1,200 V	1,200 V	1,000 V	1,200 V	1,200 V	1,000 V	1,000 V
	DC	1,000 V	1,700 V	1,000 V	1,700 V	1,700 V	1,000 V	1,700 V	1,700 V	1,000V	1,000 V
	AC+DC						1,000 V	1,700V peak	1,700V peak	1,000 V	1,000 V
Hz	●		●			●			●		
Ω / ●) / →	●		●			●			●		
T°(°C/°F)	●		●			●			●		
Adapter function			●								
2-wire phase rotation						●					
W,var,VA,PF (1F x S3F)						●			●		
THDf / THDr						●			●		
Harm0 ... Harm25						●			●		
Min / Max (100 ms)	●		●			●			●		
Peak (1.5 ms)	●		●			●			●		
True InRush	●		●			●			●		
RELative funct. (ΔX & ΔX/X)						●					
DataLog / PC Soft / LV / apk						●			●		
IP54	●		●			●			●		
IEC/EN 61010 IEC/EN 61010-2-033	600V CAT IV	1000V CAT IV 1500V CAT III	600V CAT IV	1000V CAT IV 1500V CAT III		600V CAT IV	1000V CAT IV 1500V CAT III		1000V CAT IV		