http://www.sefram.fr



# SEFRAM 56

## **Voltage tester**

### Easy to use

The new SEFRAM 56 LCD Voltage tester is an easy-to-use instrument: direct reading of all information with large digits on LCD and bargraph.

#### Safety

The new SEFRAM 56 has been designed, tested and approved according to the EN61243-3 (2010) standard. Designed with IP2X test probes, the user will be protected in any cases, including misuse of the instrument. The SEFRAM 56 is rated: CAT III - 1000V and CAT IV - 600V.

Specifications	
AC - DC voltage (EN61243-3 : 2010)	
Voltage range	12 to 750V AC/DC
Display	LCD 3 digits with polarity
AC/DC detection	Automatic, beeper for AC
Accuracy	±(1.3% +5d) in AC
	and $\pm (1.0\% + 2 \text{ in DCd})$
Response time	< 0.1s bargraph, 2s for readings
Bandwidth	DC, 45-65Hz
DDR tripping test (10mA, 30mA)	
Method	current pulled to earth
Test current after 5s	< 3.5mA
Peak current	< 0.2A
Test duration	30s
Recovery time	10mn
Continuity test	
Threshold	< 200k ohms
Resistance test	
Range, accuracy	2k ohms, ±(2% +10d)
Diode test	0,1 to 1,8V with 0,1V resolution
Frequency	
Range, accuracy	30-999Hz, ±(0,3% +5d)
Phase rotation test	
Range	100 to 750V AC
Method	measure between 2 phases, instrument in hand

Additional functions

light-up with LED of measurement area

General specifications	
Display	LCD, 3 digit and bargraph
Power supply	2 x 1.5V LR03 / AAA batteries
Protection level	IP65
Test probes	4mm IP2X, with retractable sleeves
Operating temperature	0° to 50°C (HR < 85% )
Storage temperature	-20°C to + 60°C
Safety	IEC 61010 CAT III 1000V
	and CAT IV 600V
Standard	EN61243-3 : 2010
Weight	235g (with batteries)
Dimensions	239 x 68 x 29 mm

Optional pouch : SC518

FTsefram56 A00 - Specifications can be updated without notice





32, rue Edouard Martel • B.P. 55 • 42009 - St Etienne cedex 2

Tel.+33 (0).4.77.59 36 81

Fax. +33 (0).4.77.57.23.23

Website: www.sefram.fr • e-mail: sales@sefram.fr

#### Other tests included

The SEFRAM 56 includes:

- continuity test with beeper
- test of DDR (<30mA)
- phase rotation
- resitance measurement and diode test
- frequency measurement



#### For assistance and ordering