

ELP/DCM98 series programmable DC electronic load

200 kW load



FEATURES

- Six high speed operation modes: CC, CR, CV, CW, CC+CV, CR+CV
- High-luminance VFD screen with 2 lines & 4 channels display channels
- Battery testing and short-circuit function
- Available of dynamic testing and rising edge and falling edge setting
- External current waveform monitor terminal
- Power-on-self-test, software calibration and standard rack mount
- Over current, over voltage, over power, over heat, reversed protection
- 1000/1200 V on request/polarity
- Soft start time setting, carrying the power supplier according to the voltage value set
- Supporting external trigger input and output
- Supporting remote voltage compensation and multidata storage
- Communication mode: GPIB/RS232/RS485/USB (Option)
- Customer specific models on request

| Model | | ELP/DCM9840 | | ELP/DCM9840B | |
|--|------------|----------------|----------------|----------------|----------------|
| Input Rating | Power | 200.000 W | | 200.000 W | |
| | Current | 0 - 1500 A | | 0 - 500 A | |
| | Voltage | 0 - 150 V | | 0 - 500 V | |
| CC Mode | Range | 0 - 100 A | 0 - 1000 A | 0 - 50 A | 0 - 500 A |
| | Resolution | 1 mA | 10 mA | 1 mA | 10 mA |
| | Accuracy | 0,1%+0,1%FS | 0,2%+0,5%FS | 0,1%+0,05%FS | 0,15%+0,2%FS |
| CV Mode | Range | 0,1 - 19.999 V | 0,1 - 150 V | 0,1 - 19.999 V | 0,1 - 500 V |
| | Resolution | 1 mV | 10 mV | 1 mV | 10 mV |
| | Accuracy | 0,03%+0,02%FS | 0,03%+0,02%FS | 0,03%+0,02%FS | 0,03%+0,05%FS |
| CR Mode (Voltage and current input value > 10% full measurement) | Range | 0,03 - 10 K Ω | 0,03 - 5 K Ω | 0,3 - 10 K Ω | 0,3 - 5 K Ω |
| | Resolution | 16 bit | 16 bit | 16 bit | 16 bit |
| | Accuracy | 0,1%+0,1%FS | 0,1%+0,1%FS | 0,1%+0,1%FS | 0,1%+0,1%FS |
| CW Mode (Voltage and current input value > 10% full measurement) | Range | 0 - 15.000 W | 0 - 200.000 W | 0 - 25.000 W | 0 - 200.000 W |
| | Resolution | 10 mW | 100 mW | 10 mW | 100 mW |
| | Accuracy | 0,1%+0,1%FS | 0,2%+0,15%FS | 0,1%+0,1%FS | 0,2%+0,15%FS |
| V Measurement | Voltage | 0 - 19.999 V | 0 - 150 V | 0 - 19.999 V | 0 - 500 V |
| | Resolution | 1 mV | 10 mV | 1 mV | 10 mV |
| | Accuracy | 0,015%+0,03%FS | 0,015%+0,03%FS | 0,015%+0,03%FS | 0,015%+0,05%FS |
| I Measurement | Current | 0 - 100 A | 0 - 1000 A | 0 - 50 A | 0 - 500 A |
| | Resolution | 1 mA | 10 mA | 0,1 mA | 1 mA |
| | Accuracy | 0,1%+0,1%FS | 0,2%+0,5%FS | 0,1%+0,05%FS | 0,15%+0,2%FS |
| W Measurement (Voltage and current input value > 10% full measurement) | Watt | 100 W | 200.000 W | 100 W | 200.000 W |
| | Resolution | 1 mW | 100 mW | 1 mW | 100 mW |
| | Accuracy | 0,1%+0,1%FS | 0,2%+0,5%FS | 0,1%+0,05%FS | 0,15%+0,2%FS |

| | |
|----------------------|---|
| Battery Test | Battery Input: 0,5 - 120 V; Max. Measurement: Capacity = 999 AH; Resolution = 0,1 mA; Time Range = 1S - 16 HS |
| Dynamic Test | Transition List: 0 - 25 kHz; 5 A/us; T1 & T2: 60 us - 999 S; Accuracy: +/- 15 % offset + 10 %FS |
| CC soft-startup Time | 1 mS; 2 mS; 5 mS; 10 mS; 20 mS; 50 mS; 100 mS; 200 mS; Accuracy: +/- 15 % offset + 10 %FS |

| | | | | | |
|---------------|---------------|------------------|----------|------------------|---------|
| Short Circuit | Current CC | = 100 A | = 1000 A | = 55 A | = 550 A |
| | Voltage CV | 0 V | | 0 V | |
| | Resistance RC | = 2,3 mΩ | | = 2,6 mΩ | |
| Temperature | Operating | 0 - 40 °C | | 0 - 40 °C | |
| | Nonoperating | -10 °C - 70 °C | | -10 °C - 70 °C | |
| Dimension | WxHxD (mm) | 600 x 1880 x 700 | | 600 x 1880 x 700 | |
| Weight | Kg | 4280 | | 4280 | |

