




Model	5 XP-A	15 XP-B	35 XP-A
			
Display	1999 digiti	1999 digiti	3999 digiti
Tensiune CA	0,1 mV...750 V	0,1 mV...750 V	0,1 mV...750 V
Precizie	(1,5% + 5 D)	(1,5% + 5 D)	(1,5% + 5 D)
Frecventa	45...500 Hz	45...500 Hz	45...500 Hz
Tensiune CC	0,1 mV...1000 V	0,1 mV...1000 V	0,1 mV...1000 V
Precizie	(1% + 1 D)	(0,5% + 1 D)	(0,5% + 1 D)
Curent CA	0,1 $\mu$ A...200 mA	1 $\mu$ A...2 A	0,1 $\mu$ A...2 A
Precizie	(2% + 5 D)	(1,5% + 5 D)	(1,5% + 5 D)
Frecventa	45...500 Hz	45...500 Hz	45...500 Hz
Curent CC	0,1 $\mu$ A...200 mA	1 $\mu$ A...2 A	0,1 $\mu$ A...2 A
Precizie	(1,5% + 5 D)	(1,2% + 3 D)	(1,0% + 2 D)
Rezistenta	0,1 $\Omega$ ... 20 M $\Omega$	0,1 $\Omega$ ... 2000 M $\Omega$	0,1 $\Omega$ ... 40 M $\Omega$
Test dioda	★	★	★
Test continuitate	★	★	★
Capacitanta			4,000 nF...4,000 mF
Frecventa			10,00 Hz...1 MHz
Temperatura			-20...1000°C
Automatic		★	★
Manual	★	★	★
Data hold	★	★	★
Min/Max	★		
Auto Power Off		★	★
Baterie	1 x 9 V	1 x 9 V	1 x 9 V
Clasa	CAT III/300 V, CAT II/600 V	CAT III/600 V, CAT II/1000 V	CAT III/300 V, CAT II/600 V
	Detectie tensiune non-contact Voltect™, Test baterie 1,5 V / 9 V, Toc cu agatatoare magnetica Magne-Grip™	Detectie tensiune non-contact Voltect™, Functie Logic Test TTL, Toc cu agatatoare magnetica Magne-Grip™	Detectie tensiune non-contact Voltect™, Toc cu agatatoare magnetica Magne-Grip™