

- measurement of resistance:  $t^\circ$  coeff.:  $\pm (0.1\% \text{ of } L + 0.5 \text{ digits}) / ^\circ\text{C}$

measurement current: 1.5 mVAC / Measurement frequency: 1 kHz  $\pm$  10 %

<i>Range</i>	<i>Resolution</i>	<i>Measurement current</i>	<i>Accuracy</i>
40 m $\Omega$	10 $\mu\Omega$	37.5 mA	$\pm (1 \% \text{ of } L + 8 \text{ digits})$
400 m $\Omega$	100 $\mu\Omega$	3.75 mA	
4 $\Omega$	1 m $\Omega$	375 $\mu\text{A}$	
40 $\Omega$	10 m $\Omega$	37.5 $\mu\text{A}$	

- measurement of voltage:  $t^\circ$  coeff.:  $\pm (0.1\% \text{ of } L + 0.5 \text{ digits}) / ^\circ\text{C}$

<i>Range</i>	<i>Resolution</i>	<i>Accuracy</i>
4 V	1 mV	$\pm (0.1 \% \text{ of } L + 6 \text{ digits})$
40 V	10 mV	